



### ELECTRICAL:

1. Impedance:  $50 \Omega$  ;
2. Frequency: DC~50GHz;
3. VSWR/Return Loss:  $\leq 1.2$ ;
4. Insertion Loss:  $\leq 0.06 \sqrt{\text{dB}}$ ;
5. Insulation Resistance:  $\geq 5000M \Omega$  ;
6. Dielectric Withstanding Voltage(AC): 500 Vrms.

### MATERIAL & PLATING:

1. Contact: Beryllium Copper, Gold;
2. Insulation: PEI;
3. Outer Conductor: Stainless steel, Passivated.

### ENVIRONMENTAL & MECHANICAL:

1. Temperature Range:  $-55^{\circ}\text{C} \sim +155^{\circ}\text{C}$ ;
2. RoHS: Compliant.

All dimensions are in mm,  
all angles are in degrees.

<b>TITLE</b>  1.0mm Female to 2.4mm Male RF Adapter		<b>PART NO.</b>	1.0/2.4-KJ1
		<b>DWG. NO.</b>	---
		<b>DATE</b>	---
<b>TOLERANCES UNLESS OTHERWISE SPECIFIED</b> X $\pm 0.50$ XX $\pm 0.10$ X $\pm 0.20$ ANGLES $\pm 1^{\circ}$		<b>SCALE</b>	<b>VIEW DIRECTION</b>
<b>SHEET: 1/1</b>		6:1	
		<b>REV.</b>	V1.0
<b>Mechanc (Shanghai) Information Technology Co., Ltd.</b>  <a href="http://www.mechanc.com">www.mechanc.com</a> <a href="mailto:sales@mechanc.com">sales@mechanc.com</a>			